

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix

		Genuine HP ProCurve SFP+ Transceivers and Cables						
HP Networking Switch Series	Product Name	Product Number	10GBASE-SR, LR, LRM	10GBASE-ER	10-GbE SFP+ Direct Attach Cables		10-GbE XFP-SFP+ Direct Attach Cables	
			(J9150A, J9151A, J9152A)	(J9153A)	1m, 3m, 7m	10m, 15m	1m, 3m, 5m	
			(J9281A, J9283A, J9285A)	(J9281B, J9283B, J9285B)	(J9286B, J9287B)	(J9300A, J9301A, J9302A)		
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
2530	2530-24G-2SFP+ Switch	J9856A	all software versions	all software versions	all software versions	all software versions	all software versions	all software versions
	2530-48G-2SFP+ Switch	J9855A						
	2530-24G-PoE+-2SFP+ Switch	J9854A						
	2530-48G-PoE+-2SFP+ Switch	J9853A						
2910al	2910al-24G Switch	J9145A	--	--	--	--	--	--
	2910al-48G Switch	J9147A						
	2910al-24G-PoE+ Switch	J9146A						
	2910al-48G-PoE+ Switch	J9148A						
	2-Port 10-GbE SFP+ al Module	J9008A						
2920	2920-24G Switch	J9726A	--	--	--	--	--	--
	2920-48G Switch	J9728A						
	2920-24G-PoE+ Switch	J9727A						
	2920-48G-PoE+ Switch	J9729A						
	2920-48G-POE+ 740W Switch	J9836A						
	2-Port 10GbE SFP+ Module	J9731A						
3500yl	Switch 3500yl-24G-PWR	J8692A	--	--	--	--	--	--
	Switch 3500yl-48G-PWR	J8693A						
	3500yl-24G-PoE+ Switch	J9310A						
	3500yl-48G-PoE+ Switch	J9311A						
	10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J9312A						
3800	3800-24G-2SFP+ Switch	J9575A	all software versions	all software versions	all software versions	all software versions	KA.15.09.0003 and later	all software versions
	3800-48G-4SFP+ Switch	J9576A						
	3800-24G-PoE+-2SFP+ Switch	J9573A						
	3800-48G-PoE+-4SFP+ Switch	J9574A						
	3800-24SFP-2SFP+ Switch	J9584A						
5400zl	4-Port 10-GbE SFP+ zl Module	J9309A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.05.0001 and later	K.14.39 and later
	8-Port 10-GbE SFP+ v2 zl Module	J9538A						
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix (cont'd)

		Genuine HP ProCurve SFP+ Transceivers and Cables						
HP Networking Switch Series	Product Name	Product Number	10GBASE-SR, LR, LRM	10GBASE-ER	10-GbE SFP+ Direct Attach Cables		10-GbE XFP-SFP+ Direct Attach Cables	
			(J9150A, J9151A, J9152A)	(J9153A)	1m, 3m, 7m	10m, 15m	1m, 3m, 5m	
			(J9281A, J9283A, J9285A)	(J9281B, J9283B, J9285B)	(J9286B, J9287B)	(J9300A, J9301A, J9302A)		
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
5400R	8-Port 10-GbE SFP+ v2 zl Module	J9538A	all software versions	all software versions	all software versions	all software versions	all software versions	all software versions
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						
	20p PoE+ /4p SFP+ v3 zl2 Module	J9990A	KB.15.17 and later	KB.15.17 and later	(not supported)	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later
	8p 1G/10GbE SFP+ v3 zl2 Module	J9993A	KB.15.17 and later	KB.15.17 and later	(not supported)	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later
6120	6120G/XG Blade Switch	498358-B21	--	--	--	--	--	all software versions
	6120XG Blade Switch	516733-B21	all software versions	(not supported)	all software versions	all software versions	Z.14.28 and later	
6200yl	Switch 6200yl-24G-mGBIC	J8992A	--	--	--	--	--	--
	10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J9312A	K.14.50 and later	K.15.02.0004 and later	K.14.50 and later	K.14.50 and later	K.15.05.0001 and later	K.14.50 and later
6600	6600-24G-4XG Switch	J9264A	K.14.03 and later	K.15.02.0004 and later	K.14.03 and later	K.14.32 and later	K.15.05.0001 and later	K.14.32 and later
	6600-24XG Switch	J9265A						
	6600-48G-4XG Switch	J9452A						
8200zl	4-Port 10-GbE SFP+ zl Module	J9309A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.05.0001 and later	K.15.02.0004 and later
	8-Port 10-GbE SFP+ v2 zl Module	J9538A						
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix (cont'd)

HP Networking Switch Series	Product Name	Product Number	Genuine HP ProCurve X2 Transceivers					Genuine HP ProCurve Optical Media Converter (OMC) for CX4 ¹ (J8439A)
			10GBASE-SR, LR (J8436A, J8437A)	10GBASE-LRM (J9144A)	10GBASE-ER (J8438A)	10GBASE-CX4 (J8440A) (J8440B/C)		
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2900	Switch 2900-24G Switch 2900-48G	J9049A J9050A	all software versions	T.13.18 and later	all software versions	all software versions	all software versions	all software versions, OMC for fixed CX4 ports only
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch 2-Port 10-GbE CX4 al Module	J9145A J9147A J9146A J9148A J9149A	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- all software versions
3400cl	Switch 3400cl-24G Switch 3400cl-48G Switch cl 10-GbE CX4 Copper Module Switch cl 10-GbE Media Flex Module	J4905A J4906A J8434A J8435A	-- -- -- M.08.54 and later	-- -- -- (not supported)	-- -- -- M.08.75 and later	-- -- -- M.08.54 and later	-- -- -- M.10.06 and later	-- -- M.08.54 and later, OMC for J8434A & J8440A/B
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR 3500yl-24G-PoE+ Switch 3500yl-48G-PoE+ Switch Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module 10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J8692A J8693A J9310A J9311A J8694A J9312A	-- -- -- -- all software versions --	-- -- -- -- K.13.20 and later --	-- -- -- -- all software versions --	-- -- -- -- all software versions --	-- -- -- -- K.11.17 and later --	-- -- -- -- all software versions, OMC for fixed CX4 ports only K.14.50 and later
4200vl	Switch vl 1-Port 10-GbE X2 Module	J8766A	L.11.08 and later	L.11.11 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later
5300xl	Switch xl 1-Port 10-GbE X2 Module	J8988A	E.11.02 and later	(not supported)	E.11.02 and later	E.11.02 and later	E.11.02 and later	E.11.02 and later
5400zl	Switch zl 4-Port 10-GbE X2 Module Switch zl 4-Port 10-GbE CX4 Module	J8707A J8708A	all software versions --	K.13.20 and later --	all software versions --	all software versions --	K.11.17 and later --	K.11.33 and later, OMC for J8708A & J8440A/B
5400R	20p PoE+/4p SFP+ v3 zl2 Module 8p 1G/10GbE SFP+ v3 zl2 Module	J9990A J9993A	-- --	-- --	-- --	-- --	-- --	-- --
6200yl	Switch 6200yl-24G-mGBIC Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module 10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J8992A J8694A J9312A	-- K.11.33 and later --	-- K.13.20 and later --	-- K.11.33 and later --	-- K.11.33 and later --	-- K.11.33 and later --	-- K.11.33 and later, OMC for fixed CX4 ports only K.14.50 and later
6400cl	Switch 6400cl (CX4) Switch 6410cl (X2) Switch cl 10-GbE CX4 Copper Module Switch cl 10-GbE Media Flex Module	J8433A J8474A J8434A J8435A	-- M.08.62 and later -- M.08.62 and later	-- (not supported) -- (not supported)	-- M.08.75 and later -- M.08.75 and later	-- M.08.62 and later -- M.08.62 and later	-- M.08.102 and later -- M.08.102 and later	M.08.62 and later, OMC for J8433A & J8440A/B M.08.62 and later, OMC for J8434A & J8440A/B
8100fl	Switch fl 1-Port 10-GbE X2 Interface Module Switch fl 2-Port 10-GbE X2 Interface Module	J8736A J8737A	CY.02.03.0005 and later CY.02.05.0001 and later	(not supported) (not supported)	CY.02.03.0005 and later CY.02.05.0001 and later	CY.02.03.0005 and later CY.02.05.0001 and later	CY.02.03.0005 and later CY.02.05.0001 and later	CY.02.03.0005 and later, OMC for J8440A/B CY.02.05.0001 and later, OMC for J8440A/B
8200zl	Switch zl 4-Port 10-GbE X2 Module Switch zl 4-Port 10-GbE CX4 Module	J8707A J8708A	all software versions --	K.13.20 and later --	all software versions --	all software versions --	all software versions --	all software versions, OMC for J8708A & J8440A/B

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix (cont'd)

HP Networking Switch Series	Product Name	Product Number	Genuine HP ProCurve XENPAK Transceivers
			Supported with This Software
9300m	9300 2-Port 10-GbE Module	J8174A	10GBASE-SR, LR, ER (J8175A, J8173A, J8176A) 07.6.04 and later
9408sl	9400sl 4-Port 10-GbE Module	J8682A	all software versions

Footnotes

¹ The J8439A Optical Media Converter is supported in the J8440A and J8440B CX4 transceivers, but not in the J8440C.

© Copyright 2014 Hewlett-Packard Development Company, L.P.
 The information contained herein is subject to change without notice.
 April 2015
 5998-8063

